SUMMIT

ZNL05P



3.75" x 29.75" x 20" (H x W x D)

30" wide gas cooktop in brushed chrome with 4 open burners and battery start ignition, made in the USA

Highlights:

Made in the USA

30" size fits popular 28 3/8" W x 18 5/8" D counter cutouts

Battery start ignition is ideal for locations without standard electrical power access

Product Features:

| Made in the USA | Designed and constructed domestically | |
|--------------------------|---|--|
| Classic 30" fit | Fits common 28 3/8" W x 18 5/8" D counter cutouts | |
| Four open burners | 9000 BTU burners with built-in enamel grates to meet most cooking needs | |
| Brushed chrome surface | Striking look with easy cleanability | |
| Recessed top | Curved design helps to contain spills on the surface | |
| Battery start ignition | Ideal alternative to pilot light sources when no power source is accessible | |
| Designed for natural gas | Set for use with natural gas connection. To convert for propane use, add Kit LP | |
| Push-to-turn knobs | Knobs require a small amount of force to ensure burners are not accidentally turned on | |
| Side controls | Cooktop knobs are located on the right side of the cooktop, clearing up space in the front for easier cooking | |







ZNL05P Specifications:

| Overview | | |
|---------------------------|--------------------------|--|
| Height of Cabinet | 3.75" (10 cm) | |
| Width | 29.75" (76 cm) | |
| Depth | 20.0" (51 cm) | |
| Cabinet | Chrome | |
| Weight | 32.0 lbs. (15 kg) | |
| Parts & Labor Warranty | 1 Year | |
| UPC | 761101043913 | |
| Gas Cooktop | | |
| Ignition | Battery Start | |
| LP Convertible | With Kit LP Accessory | |
| Number of Burners | 4 | |
| Controls | Dial | |
| Surface | Painted | |
| Cutout Width | 28.38" (72 cm) | |
| Cutout Depth | 18.63" (47 cm) | |
| Burner #1 BTU | 9000.0 | |
| Burner #2 BTU | 9000.0 | |
| Burner #3 BTU | 9000.0 | |
| Burner #4 BTU | 9000.0 | |
| Power Cord Included | No | |

